

HS321S

Wireless quick start home alarm

Reliable and hassle-free, the HS321S Wireless quick start home alarm is great for families who want to keep things simple. You can protect two rooms and two doors or windows with the included accessories, and the wireless remote control key fobs make it easy to control your alarm from up to 150m away.

**Both HS321S and HS321N are identical and interchangeable, the only difference are the other European languages on the packaging.*

,



Pack Contents:

1 x Wireless Battery Siren, 2 x Wireless Motion Sensor (PIR), 2 x Wireless Door and Window Sensor, 2 x Wireless Remote Control Key Fob, 3 x Security Window Stickers, 4 x LR20 (D) 1.5V Battery, 6 x LR03 (AAA) 1.5V Battery, 4 x CR2032 (3V) Battery, 1 x Quick Start Guide, 1 x Safety & Guarantee, 1 x Declaration of Conformity,

Key Features and Benefits:

Quick Start Alarm Kit - Specifically designed for smaller houses, Honeywell's Quick Start Alarm Kits are incredibly easy to set up and use. There's no keypad to operate, so simply install the siren, motion sensors, and door and window sensors and you're ready to go.

Peace of mind - Leave your home safe in the knowledge that it's protected by your Honeywell home alarm. Wireless external sirens provide a visible deterrent with flashing LEDs and a loud 105dB alert in emergencies, and should anything happen while you're away, Event and Tamper Alerts will let you know if the alarm has been triggered or tampered with.

Easy to use - Control your Honeywell home alarm with ease from anywhere inside or outside your home, up to 150m away. For additional peace of mind, there's even a panic button you can use to activate your alarm in case of emergencies.

Easy to maintain - With a long battery life of up to two years, you won't need to worry about your Honeywell Home Alarm after you have installed it. Conveniently located low battery indicators on each accessory will notify you when it's finally time to change the batteries, and the easy-open battery compartments makes the process as easy as 1-2-3.

Reliability and quality - Honeywell ActivLink®, using the 868MHz frequency, is our innovative wireless protocol which delivers greater range capability of up to 200m, extended battery life of up to 2 years, and improved connection reliability with no false triggering, all supported by our 2 year product quality guarantee.

Flexible and expandable - Add up to 12 wireless motion sensors or door and window sensors to protect every area of your home, and link up to 6 remote control key fobs so the entire family can control your Honeywell home alarm.

Easy To Install - Honeywell Home Alarm Kits have been designed to be easily installed, with all the accessories pre-linked and ready to go out of the box. All fixings and batteries are also included, so there's nothing more to buy, and there's even optional screw-free installation on most accessories with the included sticky pads. All this is backed up by our 2 year product guarantee.

Specification:

Wireless Battery Siren	
Colour	White
Wall mounted	Yes
Frequency / Wireless Range*	868MHz / 200m
Audible Range (Volume)	250m (105dB)
Melodies	1
Alarm Time (minutes)	1 or 3 (Control Unit mode), 3 or 10 (Siren mode)
Visual Alerts	Comfort LEDs
Power	Battery: 4 x LR20 (D) 1.5V - (included)
Battery Life (Years)	1.5
Battery Features	Low Battery Indicator
Maximum Device Capacity	12 x Wireless Motion Sensor (PIR)/Wireless Door and Window Sensor, 6 x Wireless Remote Control Key Fob (Control Unit mode)
Security Features	Control Unit Mode: 1 Security Zone /Alarm Lockout /Auto Reset / Event Alerts /15s Entry/Exit Delay, + Siren Service Mode
Security Functions	Arm/Disarm/Delay Arm/Panic Alarm (Control Unit mode)
Tamper Protection	Yes
Factory Reset	Yes
IP Rating	IP44
Operating Temperature/Storage Temperature	-20°C to +50°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	297 (h) x 190 (w) x 108 (d) / 1270 (g)
Fixings	Brackets / Rawl Plugs / Screws

Wireless Motion Sensor (PIR) (x 2)	
Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Wireless Range*	868MHz / 200m
Power	Battery: 3 x LR03 (AAA) 1.5V - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Detection Range / Angle	12m / 105°
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	81 (h) x 61 (w) x 48 (d) / 75 (g)
Fixings	Brackets / Rawl Plugs / Screws / Sticky Pads

Wireless Door and Window Sensor (x 2)

Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Wireless Range*	868MHz / 200m
Power	Battery: 1 x CR2032 (3V) - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	71 (h) x 40 (w) x 14 (d) / 28 (g)
Fixings	Screws / Sticky Pads

Wireless Remote Control Key Fob (x 2)

Colour	Black
Frequency / Wireless Range*	868MHz / 150m
Visual Alerts	Confidence Light
Power	Battery: 1 x CR2032 (3V) - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Security Functions	Delay Arm/Disarm/Home mode/Panic Alarm (with Keypad) or Arm/Disarm/Delay Arm/Panic Alarm (with Siren)
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	62 (h) x 33 (w) x 14 (d) / 16 (g)

Pack

EAN Code	5004100966568
Pack Dimensions (mm) / Weight (g)	325 (h) x 177 (w) x 405 (d) / 3500 (g)
Standard Pack Quantity	3

* Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.