

## HS3PIR1S

### Wireless motion sensor (PIR)

Protect more rooms in your home by expanding your Honeywell home alarm system with a HS3PIR1S Wireless motion sensor. It monitors each room with a wide 105 degree sensing angle, and triggers the alarm when movement is detected.

*\*Both HS3PIR1S and HS3PIR1N are identical and interchangeable, the only difference are the other European languages on the packaging.,*



### Pack Contents:

1 x Wireless Motion Sensor (PIR), 3 x LR03 (AAA) 1.5V Battery, 1 x Quick Start Guide, 1 x Safety & Guarantee, 1 x Declaration of Conformity,

### Key Features and Benefits:

**Flexible and expandable** - Add up to 44 accessories or devices to your system, and activate and control up to 3 separate zones to suit your lifestyle and needs.

**Easy To Install** - All Honeywell push buttons and accessories are easy to install, with optional screw-free installation and an easy open battery compartment so you can be set up in minutes. All this is backed up by our 2 year product guarantee.

### Specification:

<b>Wireless Motion Sensor (PIR)</b>	
Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Wireless Range*	868MHz / 200m
Power	Battery: 3 x LR03 (AAA) 1.5V - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Detection Range / Angle	12m / 105°
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	81 (h) x 61 (w) x 48 (d) / 75 (g)
Fixings	Brackets / Rawl Plugs / Screws / Sticky Pads

<b>Pack</b>	
EAN Code / Standard Pack EAN Code	5004100966025 / 5004100966186
Pack Dimensions (mm) / Weight (g)	60 (h) x 75 (w) x 140 (d) / 170 (g)
Standard Pack Quantity	6

\* Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.