

LED Filament GLS Dimmable




Energy saving LED GLS replacement lamp featuring LED filament technology to closely resemble the look and feel of a traditional incandescent lamp.

- Available in 5W (4-filaments) or 7.5W(6-filaments)
- 5W = 15,000 hour life, 7,500 switching cycles
- 7.5W = 10,000 hour life, 5,000 switching cycles
- 2700K warm white
- BC-B22d or ES-E27 cap
- Clear finish
- Dimmable - DuoDim™ Technology compatible with both leading and trailing edge dimmers*
- For indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Initial Lumens (lm)	Incandescent Equivalent (W)	Dimensions (mm)		Energy Rating	Order Qty
								Dia	H		
Single Carton											
4184	5	240	BC-B22d	Warm White	2700	470	40	60	104	A+	1
4191	5	240	ES-E27	Warm White	2700	470	40	60	104	A+	1
4207	7.5	240	BC-B22d	Warm White	2700	806	60	60	104	A+	1
4214	7.5	240	ES-E27	Warm White	2700	806	60	60	104	A+	1

* The lamp is compatible with most dimmer switches, please refer to website for up-to-date list of compatible dimmer switches.



We have valued our reputation since 1878, why risk yours with anyone else?

5W LED Filament GLS Dimmable

Part Codes: 4184, 4191



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-5	Steps from 0-50%
Aurora	AU-DSP651	75W-650W	Leading	1-5	Steps from 0-50%
Aurora	AU-DSP400X	60W-400W	LED	1-5	Does not dim below 5%
Danlers	DSS1D 250W	40W-250W	Leading	1-5	Steps from 0-50%
Danlers	DP1D 400W1ET	60W-400W	Leading	1-5	Steps from 0-60%
Danlers	DPDLED	5W-250W	Leading	1-5	Steps from 0-50%
MK	K451 1xxxLV	40W-220W	Leading	1-5	Does not dim below 25%
MK	K1521WHILV	40W-300W	Leading	1-5	Does not dim below 25%
MK	K1524WHILV	40W-300W	Leading	1-5	Does not dim below 20%
Zano	ZANOMO500	11W-50W	Leading	1-5	Steps from 0-50%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-5	Does not dim below 15%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-5	Does not dim below 15%
Eaton	P9131	60W-250W	Leading	1-5	Steps from 0-40%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W, DQDGEU400W

We have valued our reputation since 1878, why risk yours with anyone else?

7.5W LED Filament GLS Dimmable

Part Codes: 4207, 4214



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-3	Steps from 0-50%
Aurora	AU-DSP651	75W-650W	Leading	1-3	Steps from 0-50%
Aurora	AU-DSP400X	60W-400W	LED	1-3	Flickers above 90%
Danlers	DSS1D 250W	40W-250W	Leading	1-3	Steps from 0-50%
Danlers	DP1D 400W1ET	60W-400W	Leading	1-3	Steps from 0-60%
Danlers	DPDLED	5W-250W	Leading	1-3	Steps from 0-50%
MK	K451 1xxxLV	40W-220W	Leading	1-3	Does not dim below 50%
MK	K1521WHILV	40W-300W	Leading	1-3	Does not dim below 40%
MK	K1524WHILV	40W-300W	Leading	1-3	Does not dim below 50%
Zano	ZANOMO500	11W-50W	Leading	1-3	Steps from 0-50%
Varilight	V-Pro JQP401W	10W-400W	Trailing	1-3	Does not dim below 40%
Varilight	V-Pro JQP252W	10W-250W	Trailing	1-3	Does not dim below 40%
Eaton	P9131	60W-250W	Leading	1-3	Steps from 0-40%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W, DQDGEU400W

We have valued our reputation since 1878, why risk yours with anyone else?